



PNP Silicon High Voltage Transistor

Features

- Epoxy meets UL-94 V-0 flammability rating unless otherwise noted)

Item	Symbol	Unit	Conditions	Value
Collector-Base Voltage	V_{CBO}	V	$I_C=-100\mu A, I_E=0$	-300
Collector-Emitter Voltage	V_{CEO}	V	$I_C=-1mA, I_B=0$	-300
Emitter-Base Voltage	V_{EBO}	V	$I_E=-100\mu A, I_C=0$	-5
Collector Current	I_C	mA		-100
Collector Power Dissipation	P_C	mW		200
Operation Junction Temperature	T_J			-55 to +150

Storage Temperature	T_{stg}	-55 to +150
---------------------	-----------	-------------

Collector-base breakdown voltage	V_{CBO}	V	$I_C=-100\mu A, I_E=0$	-300	
Collector-emitter breakdown voltage	V_{CEO}	V	$I_C=-1mA, I_B=0$	-300	
Emitter-base breakdown voltage	V_{EBO}	V	$I_E=-100\mu A, I_C=0$	-5	
Collector-base cut-off current	I_{CBO}	nA	$V_{CB}=-200V, I_E=0$		-250
Emitter-base cut-off current	I_{EB}	nA	$V_{EB}=-200V, I_C=0$		-10
DC current gain	h_{FE}		$V_{CE}=-10V, I_C=-10mA$	mA 6	
	h_{FE}		$V_{CE}=-10V, I_C=-10mA$	0mA	10
	h_{FE}		$V_{CE}=-10V, I_C=-10mA$	0mA 6	

Collector-emitter saturation voltage	$V_{CE(sat)}$	
--------------------------------------	---------------	--



MMSTA92

RoHS
COMPLIANT

■Other Characteristics $T_a=25$ Unless otherwise specified

Item	Symbol	Unit	Conditions	Min	Max
Transition frequency	Ft	MHz	VCE=-20V, IC=-10mA, f=30MHz	50	

■

0067\$

v627 3DFNDJH 2XWOLQH 'LPHQVLRQV

v627 6ROGHULQJ)RRWSULQW



Disclaimer

The information presented in this document is for reference only. Yangzhou Yangjie Electronic Technology Co., Ltd. reserves the right to make changes without notice for the specification of the products displayed herein to improve reliability, function or design or otherwise.

The product listed herein is designed to be used with ordinary electronic equipment or devices, and not designed to be used with equipment or devices which require high level of reliability and the malfunction of which would directly endanger human life (such as medical instruments, transportation equipment, aerospace machinery, nuclear-reactor controllers, fuel controllers and other safety devices), Yangjie or anyone on its behalf, assumes no responsibility or liability for any damages resulting from such improper use of sale.

This publication supersedes & replaces all information previously supplied. For additional information, please visit our website [http:// www.21yangjie.com](http://www.21yangjie.com) , or consult your nearest Yangjie's sales office for further assistance.